



Number of inputs		4 SAT, 1 TER
Subscriber outputs		8
Connectors	F-con	female
Frequency range SAT	MHz	950-2150
Frequency range TER	MHz	47-862
Gain SAT	dB	2
Gain TER	dB	4
Isolation TER to SAT	dB	25
Isolation SAT to TER	dB	28
Isolation cross polarisation HV	dB	28
Isolation out - out TER	dB	28
Isolation out - out SAT	dB	35
Return loss SAT inputs	dB	11
Return loss SAT outputs	dB	9
Return loss TER inputs	dB	11
Return loss TER outputs	dB	9
Output level SAT (IMD <sub>3</sub> - 35 dB)	dBμV	101
Output level TER (IMD <sub>3</sub> - 60 dB)	dBμV	85
Impedance input/output	Ohm	75
Switching	VDC	13V -18V 13V/22kHz 18V/22 kHz
Stand-by power consumption	W	max 2

- Multischalter mit 5 Eingängen (4x SAT, 1x terr) und 8 Receiver Ausgängen, QUAD-LNB tauglich

- 5 Eingänge (4 x SAT, 1 x terr.)  
- 8 Ausgänge

- HDTV- und Quadtauglich  
- Schaltnetzteil  
- SAT: aktiv  
- Terrestrisch: passiv

- F-Anschlüsse  
- LED-Betriebsanzeige  
- Erdungsanschluß

- RoHS-konform

- multiswitch with 5 inputs (4x SAT, 1x terr.) and 8 outputs for receiver, QUAD-LNB compatible

- 5 Inputs ( 4 x SAT, 1 x terr.)  
- 8 Outputs

- Compatible with HDTV and Quad-LNB  
- switching power supply  
- active satellite path  
- passive terrestrial path

- F-connector  
- LED-operating mode  
- ground connection

- RoHS-compliant

### Änderungen

Datum	Name	gez.:	Datum	Name
		gef.:	25.08.2011	tf
		gepr.:	25.08.2011	tf
		Norm.:		

Bezeichnung

**SAT Multiswitch 5/08  
MS-508PQ**

Blatt

Zeichnungs-Nr.:

**67261**

von